

Prism Systems International, Inc.

Prism Message Gateway Keypad Commands

Subscriber Command Mode

- * Enter Security Code for Subscriber Options

Main Menu

- 7 Play Messages Menu
 - 7 Review First Messages
 - 3 Delete Message
 - 4 Scan Messages
 - 5 Save Message
 - 6 Skip Back 2-4 Seconds
 - 7 Replay This Message
 - 8 Play Time and Date of Current Message
- * (While message is playing)
 - 7 To Transfer This Message With Comment
Record Comment Then Press #
Input Mailbox Number To Transfer This Message To
 - 2 To Accept and Send Message
 - 3 To Enter a Different Mailbox Number
 - # To Quit and Return to User Options
 - 8 To Transfer This Message Without Comment
Input Mailbox Number to Transfer This Message To
 - 2 To Accept And Send Message
 - 3 To Enter a Different Mailbox Number
 - # To Quit and Return to User Options
- 8 User Options
 - * To Leave a Message in Another Mailbox
Record Your Message Then Press #
 - 2 To accept and Save Message
 - 3 To Enter a Different Mailbox Number
 - # To Quit and Return to User Options
 - 4 Record a Personal Greeting
Record Your Greeting Then Press #
 - 2 To Accept and Save Greeting
 - 3 To Discard and Record a Different a Greeting
 - 5 Listen to Your Recording
 - # To Quit and Return to User Options
 - 6 Record Your Name Tag
Record Your Name Then Press #
 - 2 To Accept and Save Name Tag

Prism Systems International, Inc.

- 3 To Re-record Your Name Tag
- 5 Listen to Your Name Tag
- # To Quit and Return to User Options

- 7 Change Your Security Code
 - Input Your New Security Code
 - 2 To Accept and Save Your Security Code
 - 3 To Enter a Different Security Code
 - # To Quit and Return to User Options

- 8 More User Options
 - 4 To Erase Your Greeting
 - 6 To Erase Your Name Tag
 - 7 To Silence Time and Date
 - 1 To Select Standard Menu – Time/Date For Each Message
 - 2 To Select Express Menu – No Time/Date
 - # To Quit and Return to User Options